



## **RFoG & GPON ONU Quad-plexer**

### **RTXM180-601**

---

#### **Features**

- *Single Fiber Quad-plexer*
- *1.25Gbps data upstream / 2.5Gbps data downstream*
- *5~42MHz RF signal upstream / 54~1002MHz CATV analog signal downstream*
- *Burst mode transmission with 1310nm DFB laser*
- *Continuous mode digital receiver with 1490nm APD-TIA*
- *Burst mode CATV return path transmission with 1610nm DFB Laser*
- *Analog CATV receiver with 1555nm InGaAs PIN detector*
- *+3.3V / +12V power supply*
- *LVPECL compatible data input*
- *CML compatible data output*
- *LVPECL transmitter burst-mode control*
- *LVTTL I2C DDM interface*
- *LVTTL TX\_SD and RX\_SD*
- *Soft Enable/Disable TX*
- *Fully RoHS Compliant*
- *All metal housing for superior EMI performance*
- *Excellent ESD/TVS protection*
- *0 °C to 70 °C operating temperature*
- *1 × 20 Pin and 2" × 2.25" Package*
- *SMB RF output connector*
- *Real time monitoring of:*
  - *Temperature*
  - *Supply voltage*
  - *Laser bias current*
  - *Transmitted optical power*
  - *Received optical power*
  - *Video Received optical power*
  - *RF Output level*

## Applications

- *RfoG+GPON ONU Side*
- *Voice/Data/Video FTTx*

## Standards

- *ITU-T G.984.2 Class B+*
- *ITU-T G.984.5*
- *C-Docsis 3.0*
- *SCTE 174 2010*
- *RoHS 6*
- *SFF-8472Rev9.5*

## Descriptions

RFoG+GPON ONU Quad-plexer Transceiver is designed for Gigabit-capable Passive Optical Network (GPON). The Quad-plexer comprise of a Burst Mode optical transmitter, a Continuous Mode optical receiver, a Burst Mode RF return transmitter and an Analog CATV forward receiver.

The Digital transmitter uses a 1310nm DFB laser diode and an integrated Burst Mode laser driver which designed to perform very small burst enable/disable delay time. The transmitter also incorporates an Automatic Power Control(APC) circuit and an Automatic Temperature Control(ATC) circuit to keep the launch optical power and extinction ratio over an operating case temperature of 0~+70°C.

The Digital receiver uses an integrated 1490nm APD photodiode and preamplifier mounted together. It has the function that indicates receiver signal-detected status (active high). The transmitter also incorporates an Automatic Power Control(APC) circuit to keep the launch optical power and extinction ratio over an operating temperature of 0~+70°C.

The RF return transmitter uses a 1610nm DFB laser diode and an Burst Mode laser driver and control loop which designed to perform very small burst enable/disable delay time. The transmitter also incorporates an Automatic Power Control(APC) circuit to keep the launch optical power over an operating case temperature of 0~+70°C.

The Analog CATV receiver uses a 1555nm PIN photodiode and a high performance RF amplifier. It contains an Automatic Gain Control(AGC) circuit to keep the output effective voltage level over an input optical power range of -6dBm~+2dBm and contains a Spectrum Balance Network(SBN) circuit to keep the output tilt over a wideband of 54MHz~1002MHz.

The Quad-plexer features a digital diagnostic and control function through a digital serial I2C interface.

## Regulatory Compliance

Feature	Test Method	Performance

## Ordering Information

Part No.	Specifications											Application	
	Package	Data rate Bandwidth	GPON Laser	Optical Power	GPON Detector	Sensitivity	RFoG Laser	AGC Range	Video Detector	AGC Range	Top		Other
RTXM180-601		TX1:1.25Gb/S											RFoG+GPON
	1×20	RX1:2.5 Gb/s	1310nm	+0.5~	1490nm	< -28dBm	1610nm	0~	1550nm	-6~	0~	DDM	ONU
	SFF	TX2: 5~42MHz	DFB	+5dBm	APD-TIA		PIN	+3dBm	PIN	+2dBm	70 °C		Quad-plexer
		RX2:54~1002MHz											

**Note :** The length of pigtail is normal 1000mm ±100mm (the length of connector is included), but can be customer for specific requirement.

WTD reserves the right to make changes to the product(s) or information contained herein without notice. No liability is assumed as a result of their use or application. No rights under any patent accompany the sale of any such product(s) or information.

Edition 2015-04-16

Published by Wuhan Telecommunication Devices Co.,Ltd.

Copyright © WTD

All Rights Reserved.